

# NOVA 4 CONNECT

4000 lumen COB LED work light for 18 V/20 V battery packs

ORIGINAL  
SCANGRIP



The powerful and sturdy NOVA 4 CONNECT features the latest COB LED technology and provides up to 4000 lumen making it a universal all-round work light for the demanding professional user.

NOVA 4 CONNECT is compatible with METABO/CAS battery system 18 V and all other 18 V/20 V battery packs from leading power tool brands by using the SCANGRIP CONNECTOR. In addition, the POWER SUPPLY can be used for direct power providing unlimited availability to light. NOVA 4 CONNECT also has an internal back-up battery securing 2.5 extra hours at 400 lumen.

With the user-friendly BLUETOOTH light control app, you get an extraordinary possibility to turn on/off and control up to four work lights through a mobile device. The built-in dimmer function enables you to adjust the light output into five different levels. This feature saves time from manual operation and increases work efficiency on a daily basis.

It is designed with a display for battery capacity and lumen output level, and supplied with a built-in power bank.

NOVA 4 CONNECT is extremely sturdy and waterproof (IP65). The design is elegant, with a carrying handle and a stand for flexible positioning and direct mounting on the SCANGRIP TRIPOD.

Bluetooth  
Light control app



**BATTERY, CHARGER, CONNECTORS AND POWER SUPPLY ARE SOLD SEPARATELY**

**SCANGRIP CONNECTORS**  
for 18 V/20 V battery packs

- BERNER - 03.6155C
- BOSCH/AMPSHARE - 03.6140C
- BOSCH GREEN - 03.6141C
- DEWALT - 03.6142C
- EINHELL - 03.6143C
- FEIN - 03.6144C
- FESTOOL - 03.6153C
- FLEX - 03.6145C
- HAZET - 03.6146C
- HIKOKI - 03.6147C
- INGERSOLL - 03.6152C
- MAKITA - 03.6148C
- MILWAUKEE - 03.6149C
- PANASONIC - 03.6156C
- RIDGID - 03.6154C
- SNAP-ON - 03.6151C
- WÜRTH - 03.6150C

**Accessories**



POWER SUPPLY  
03.6123C

CAS BATTERY  
18 V 5.2 Ah  
03.6121

CAS CHARGER  
03.6122



DESIGNED BY  
SCANGRIP  
IN DENMARK



Use POWER SUPPLY  
for direct power

**TECHNICAL SPECIFICATIONS**

High efficiency COB LED  
160 lm/W  
600-6000 lux@0.5m  
4000 lm@100% / 3000 lm@75% / 2000 lm@50% /  
1000 lm@25% / 400 lm@10%  
Compatible with METABO/CAS battery system 18V  
and all other 18 V/20 V battery packs by using the  
SCANGRIP CONNECTOR  
Operating time: 3-31h @18V 5.2 Ah battery, Backup:  
2.5h @400 lm  
IK07  
IP65, IP54 with battery cover  
2.35 kg  
263x230x119 mm

**JUST CONNECT**

Add the connector matching  
your battery pack



**NOVA 4 CONNECT**

Item no. 03.6101C